## **PENTEK**® Submersible Motor Controls





Pentek\* offers a full range of 1/2 - 5 HP models that are interchangeable with existing motor controls for Capacitor Start/Induction Run (CSIR) and Capacitor Start/Capacitor Run (CSCR) applications. Pentek is the professional choice in harsh and high temperature installations.

#### **APPLICATIONS**

■ Water systems... for residential, commercial, multiple housing and farm uses, where a submersible 3-wire motor is used.

### **FEATURES**

#### **ENCLOSURE**

**Rugged NEMA 3R enclosure –**Suitable for indoor/outdoor use.

**NEW HardBond**<sup>™</sup> **Finish –** 5-times more corrosion-resistant.

#### **Multiple-size Electrical Knockouts**

#### **INTERNALS**

High-load Voltage Relay Heavy-duty Contacts External Access to Overload Reset CSCR Heavy-duty Terminal Connectors – Suitable for up to #4 AWG wire.

**Industry Standard Wiring Connections –** Easy-to-read wiring diagrams.

**Agency Approvals –** CSA CUL Recognized (60 Hz)

# **PENTEK**® Submersible Motor Controls

ORDERI	NG INFOR	MATION						
НР	kW	PH	Volts	60 Hz Catalog Number	50 Hz Catalog Number	Weight		
						Lbs	Kg	Enclosure Size
CSIR - Capa	citor Start/Inc	duction Run					•	
1/2	0.37	1	115	SMC-IR0511 (-6pk)*		4	1.8	А
1/2	0.37	1	230	SMC-IR0521 (-6pk)*		4	1.8	А
3/4	0.55	1	230	SMC-IR0721 (-6pk)*		4	1.8	А
1	0.75	1	230	SMC-IR1021 (-6pk)*		4	1.8	А
CSCR - Cap	acitor Start/C	apacitor Run						`
1/2	0.37	1	230	SMC-CR0521 (-6pk)*	SMC5-CR0521	5	2.3	А
3/4	0.55	1	230	SMC-CR0721 (-6pk)*	SMC5-CR0721	5	2.3	А
1	0.75	1	230	SMC-CR1021 (-6pk)*	SMC5-CR1021	5	2.3	А
1-1/2	1.1	1	230	SMC-CR1521	SMC5-CR1521	7	3.2	В
2	1.5	1	230	SMC-CR2021	SMC5-CR2021	7	3.2	В
3	2.2	1	230	SMC-CR3021	SMC5-CR3021	7	3.2	В
5	3.7	1	230	SMC-CR5021	SMC5-CR5021	8	3.6	В
CSCR PLUS	- Capacitor S	tart/Capacito	r Run PLUS M	lagnetic Contactor				
2	1.5	1	230	SMC-CRP2021	SMC5-CRP2021	7	3.2	В
3	2.2	1	230	SMC-CRP3021	SMC5-CRP3021	8	3.6	В
5	3.7	1	230	SMC-CRP5021	SMC5-CRP5021	12	5.4	С

<sup>\*</sup>Submersible Motor Controls are available in single and six packs. Include the suffix "-6pk" after the catalog number if 6 packs are required.



