GILLETTE GENERATORS LEADER IN BRUSHLESS TECHNOLOGY

MODEL GPE-95EV

60 HERTZ

Heavy Duty, long lasting portable power for contractor and rental use. If you want clean, dependable emergency electric power, with the most reliable engines, then GEN-PRO is the right choice for you. These generator sets driven by EPA Certified engines are made for the tough jobs when you need the reliability, and good clean emergency. This is exactly what you get, when you choose GEN-PRO, because of it's many heavy duty & exclusive features.

GENERATOR MODEL	GPE-95EV
MAX. KW @ 1 PH.	9.5
PRIME KW @ 1 PH.	8.5
PRIME AMPS @ 120 V.	70
PRIME AMPS @ 240 V.	35
GENERATOR REGULATION	5 % VOLTAGE REGULATION ON SINGLE PHASE GEN-SETS.
FREQUENCY REGULATION	5 %, (3 HERTZ) FREQUENCY REGULATION FROM NAME PLATE RATING
"KLEEN-POWER"™	WAVEFORM DISTORTION IS LIMITED TO JUST 6 % ON ALL GEN- PRO GENERATOR SETS
ENGINE MODEL (WARRANTY)	VANGUARD / BRIGGS 479 V-TWIN O.H.V. (3 YEARS)
ENGINE START METHOD	12VDC ELECTRIC ONLY
ENGINE HP @ 3600 RPM	16 HP
ENGINE DISPLACEMENT	2 CYLINDER, 29.23 CU. IN. (479 CC)
ENGINE AIR CLEANER	HEAVY DUTY, LOW PROFILE, DUAL ELEMENT FILTERS
ENGINE FUEL TANK	7 GAL. (26.5 L.) METAL FUEL TANK WITH GAUGE, TWIST-CAP, & SLOSH VALVE
ENGINE OIL SYSTEM	FULL PRESSURE W/ SPIN ON OIL FILTER
LOW OIL PROTECTION	AUTOMATIC ENGINE SHUTDOWN PROTECTION AT LOW OIL LEVEL
db(A) AT 7 METERS	80
3/4 LOAD RUN TIME (HRS)	8.0
FUEL USE, GAL/LTR/HR	0.87 / 3.29
MOTOR START POWER	3 HP, CODE G ELECTRIC MOTOR
CRANE PICK-UP HOOK	OPTIONAL EQUIPMENT : CENTRAL PICK-UP ON TOP OF GEN-SET
2-WHEEL DOLLY KIT	OPTIONAL EQUIPMENT : COMPLETE WITH (2) HANDLES AND "NEVER GO FLAT" WHEELS
MAINLINE CB	♦ EXCLUSIVE: GFCI PLUS OVERLOAD CIRCUIT BREAKER PROTECTION
HOUR METER	HOUR METER WITH (3) MAINTENANCE ALERTS
POWER RECEPTACLES	(4) NEMA 5-15R, (1) L5-30R 120 VOLTS, AND (1) 14-50R 240 VOLTS RECEPTACLES
PROTECTIVE ROLL FRAME	RUGGED 1-1/4" ROUND ROLL FRAME, PROTECTING ENTIRE GEN-SET
LENGTH, INCHES	38
WIDTH, INCHES	26
HEIGHT, INCHES	28
SHIP WEIGHT, LBS.	280
CU. FEET SHIP BOX	20

♦ GFCI, GROUND FAULT CIRCUIT INTERRUPTER ON ALL 120 AND 240 VOLT RECEPTACLES.

VE ELKHART, IN 46514 USA E-mail : sales@gillettegenerators.com TEL. (574) 264 - 9639 FAX (574) 262 - 1840